

## CLAIMS

What is claimed is:

- 5
1. In a hearing aid a condenser microphone formed of a diaphragm comprised of a metallic film on a plastic substrate which extends laterally adjacent to a generally planar surface of a hearing aid housing and a backplate disposed adjacent to the diaphragm, one or more openings in the planar surface permitting sound waves to impinge on said diaphragm, said diaphragm being divided into a plurality of active diaphragm areas, to convert diaphragm vibrations, from the active areas, caused by sound impinging on said areas, into electrical impulses which are spatially coupled from the backplate to signal processing electronics.
- 10
2. A hearing aid as in claim 1, wherein said microphone is an electret type microphone.
3. A hearing aid as in claim 1, wherein bumps on said backplate functionally divide said diaphragm into dissimilar shaped active diaphragm portions.
- 15
4. A hearing aid as in claim 1, wherein said backplate functionally divides said diaphragm into active diaphragm portions of dissimilar sizes
- 20
5. A hearing aid comprising an electret microphone formed of a metallic coated diaphragm laterally disposed at one end of a housing opposite a backplate and wherein said housing includes an inwardly extending sidewall and a front wall partly enclosing a back chamber which is acoustically sealed by a printed circuit board laterally extending across and contacting a periphery of said sidewall at an open end of the housing, and wherein electronic components for the hearing aid are located on said printed circuit board and an electrical connection is formed

Sub  
a3

between said backplate and a component on a first side of the printed circuit board.

5

6. A hearing aid as in claim 5, wherein said electrical connection comprises an elongated resilient conductive member which at one end thereof is fastened to the printed circuit board and makes resilient electrical contact at the other end thereof with the backplate.

Sub  
a3

10

7. A hearing aid as in claim 6, wherein the elongated resilient conductive member is fastened to the backplate by electrically conductive epoxy.

8. A hearing aid as in claim 6, wherein the elongated resilient conductive member is added to or formed in the backplate.

9. A hearing aid as in claim 6, wherein said elongated resilient member is made of beryllium copper.

15

10. A hearing aid as in claim 5, wherein said electrical connection includes a buffer/amplifier which is connected between the backplate and the printed circuit board component.

11. A hearing aid as in claim 6, wherein the resilient member is made of a .001" thick copper foil, which includes a base which is soldered to the printed circuit board and a bent-up portion integrally projecting from the base to make contact with the backplate in assembly.

20

12. A hearing aid as in claim 11 wherein the backplate includes an electrically conductive epoxy dot applied to the backplate on its underside facing the printed circuit board so that the resilient member bent-up portion penetrates the conductive epoxy dot in assembly.

13. A hearing aid as in claim 11, where the bent-up portion of the resilient member is gold-plated to facilitate retention of contact with the backplate during use.
14. A hearing aid as in claim 11, wherein the backplate includes a depression in the backplate to accommodate the resilient member contact.
15. A hearing aid as in claim 6, wherein the resilient member is made of a metallic wire with a ring-shaped formation soldered to the printed circuit board and including a lead portion projecting from the ring and contacting the backplate in assembly.
16. A hearing aid as in claim 5, wherein said electrical connection comprises a first electrically conductive epoxy dot deposited on the backplate and a second electrically conductive epoxy dot aligned with the first electrically conductive epoxy dot and deposited on the printed circuit board so dimensioned that the epoxy dots press into each other and fuse and amalgamate to make an electrical contact during assembly.
17. A hearing aid as in claim 5 wherein said electrical connection comprises a lanced member formed in said backplate to project towards the printed circuit board, and an electrically conductive epoxy dot formed on said printed circuit board, in such a manner that the lanced member penetrates said epoxy dot and sets in that manner to maintain continued electrical contact during use.
18. A hearing aid as in claim 5 where said electrical connection comprises a relatively small plastic cube formed on electrically conductive leads which are wrapped around and project from the cube, the cube being fastened to the printed circuit board with an electrically conductive lead projecting from the cube to contact the backplate electrode to make said electrical connection.

Sub  
a3

- 5
19. A hearing aid microphone diaphragm comprising a metallic coated membrane having a front face and a back face, and a backplate mounted opposite the back face of the diaphragm and having a plurality of members which contact the membrane to define locations of a plurality of active diaphragm areas which are formed out of the single diaphragm and which produce a combined output for coupling to electrical components of the hearing aid.
20. The hearing aid microphone diaphragm of claim 19 in which the combined output has at least two fundamental resonant frequencies.
21. The diaphragm of claim 19 having plural dissimilar shaped active diaphragm areas.
22. The diaphragm of claim 19 having plural dissimilar sized active diaphragm areas.
23. The diaphragm of claim 19 having four sector-shaped active diaphragm areas and a central circular active diaphragm area.
- 15
24. In a hearing aid, a microphone formed of a diaphragm and a backplate extending in a plane adjacent to each other and proximate and parallel to a surface of a faceplate of a hearing aid enclosure, the microphone contained in a housing and wherein a plurality of sound openings are formed in the faceplate of the enclosure for admittance of acoustic waves which are transduced by said microphone into electrical impulses and coupled from said backplate to signal processing circuits in a said housing.
- 20
25. The hearing aid of claim 24 wherein said openings are flared on one or more surfaces thereof to reduce wind turbulence.

Sub  
a3

10

- 5
26. The hearing aid of claim 24 wherein vibration isolation material is disposed between the housing and the proximate enclosure surface.
27. The hearing aid of claim 26 wherein the material also has acoustic damping properties selected to dampen certain frequency resonance responses of the microphone.
28. A low noise microphone transducer having electrically adjustable sensitivity.
29. The transducer of claim 28 in which a sensitivity is controlled by changing a voltage applied to a diode coupled to a voltage divider circuit driven by a signal output of the transducer.
- 10
30. A low noise microphone transducer having a large diaphragm which drives a voltage divider circuit including a series of capacitors and transistors switches for controlling the capacitance of the circuit, thereby, to control the sensitivity of the transducer.
- 15
31. The hearing aid of claim 5 in which the circuit board is formed of a glass epoxy substrate.
32. A low noise microphone transducer having a large diaphragm which drives a voltage divider circuit including a variable capacitance diode.
33. The transducer of claim 32 in which a sensitivity of the transducer is controlled by changing a voltage applied to the diode.
- 20
34. A low noise microphone transducer having a large diaphragm which drives a voltage divider circuit including a series of capacitors and transistors switches for

Sub  
a3

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000

controlling the capacitance of the circuit, thereby to control the sensitivity of the transducer.

35. The hearing aid of claim 5 in which the back chamber is subdivided by an additional circuit board extending laterally across the sidewalls of the housing.

5 36. A hearing aid comprising:

a hearing aid enclosure;

a housing of lateral width "W" and longitudinal length "L" disposed at a proximal end of said enclosure, a transducer formed of a diaphragm comprising an electrically conductive membrane disposed opposite a conductive backplate, said membrane and diaphragm extending in a plane parallel to and proximate to and opposite a faceplate of said enclosure having sound openings formed through said faceplate.

37. The hearing aid of claim 36 wherein the housing is electrically conductive and is formed of a front surface open to a said faceplate and a sidewall extending longitudinally inward from said faceplate; a PCB having a conductive ground plane extending across said sidewall in electrical communication with the housing to form an acoustic seal for the transducer; electrical components to process signals generated by said transducer provided on said PCB; and wherein said housing and PCB form an EMI shield around said components and transducer.

38. The hearing aid of claim 36 wherein the ratio of the area of the housing opposite the faceplate to the area of the faceplate is at least 0.5.

39. The hearing aid of claim 36 wherein the housing has a greater lateral dimension than longitudinal dimension.

Sub  
a3  
10

10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100

- 5
40. A microphone assembly for a hearing aid comprising a diaphragm having a front face and a back face; a backplate laterally disposed adjacent to said diaphragm; an electrically conductive housing having a front surface proximal to said front face, the housing having a lateral opening at a distal end which is acoustically sealed by a first PCB having a ground plane extending across said opening to form a back chamber, the ground plane being in electrical contact with said housing to provide an EMI shield for an electrical components on said PCB.

- Sub  
a3
- 10
41. The assembly of claim 40 wherein the components include signal processing components for the hearing aid.

42. The assembly of claim 40 wherein the components include an integrated circuit which performs a buffer and amplification function.

- 15
43. The assembly of claim 40 wherein an additional PCB having a ground plane extending across sidewalls of the housing and in electrical contact thereto is disposed proximally adjacent to said backplate, said additional PCB having a buffer circuit disposed therein with an electrical connection from said backplate to an input to said buffer circuit.

- 20
44. A method of forming a hearing aid microphone comprising the steps of:

providing a diaphragm formed of a metallic film on a plastic substrate, extending the diaphragm laterally adjacent to a generally planar surface of a hearing aid enclosure;

providing a backplate adjacent to the diaphragm;

forming openings in the planar surface to permit sound waves to impinge on said diaphragm;

functionally dividing said diaphragm into a plurality of diaphragm areas, to convert diaphragm vibrations from the active areas caused by sound impinging on said areas into electrical impulses; and

25

CLs 94-50 5354  
O.K. for 10-79  
29/554  
K25 9/28/09

45. A method as in claim 44, wherein bumps are provided on said backplate to functionally divide said diaphragm into active diaphragm portions.

5

Sub  
a3

10

$$\frac{d}{dt} \left( \frac{\partial L}{\partial \dot{x}} \right) = \frac{\partial L}{\partial x}$$

15

47. A method as in claim 46, wherein said electrical connection comprises an elongated resilient member including the step of fastening one end thereof to the printed circuit board in an electrically conductive manner and makes resilient electrical contact at the other end thereof with the backplate electrode.

20

providing a single diaphragm by coating metal on a membrane having a front face and a back face;

mounting a backplate opposite the back face of the membrane;

contacting the membrane with a plurality of members on the backplate to

25

define locations of a plurality of active areas to produce signal outputs;

spatially combining the outputs; and



coupling the outputs to electrical components of the hearing aid.

49. A method of forming a hearing aid comprising the steps of:

forming a microphone by providing a large area diaphragm and a backplate extending in a plane adjacent to each other, disposing the diaphragm and backplate proximate to a surface of a microphone enclosure, forming sound openings in the enclosure opposite the diaphragm for admittance of acoustic waves which are transformed by said microphone into electrical impulses at said backplate, coupling the impulses from said backplate to signal processing circuits in the enclosure.

5

Sub  
a3

10

50. A method of providing a low noise microphone transducer comprising the steps of forming a large diaphragm; driving a voltage divider circuit with said diaphragm, providing a series of capacitors and transistors switches for controlling the capacitance of the circuit, thereby, to control the sensitivity of the transducer.

15

51. The method of claim 41 wherein the diaphragm is subdivided into smaller areas by a diaphragm support member.

52. The method of claim 51 wherein the diaphragm is glued to the support members.

53. The method of claim 45 in which ridges are provided on said backplate to functionally divide said diaphragm into active diaphragm portions.

54. The method of claim 45 in which the diaphragm areas are non-circular in shape.

20

55. The hearing aid of claim 24 in which the housing has a front face located opposite the plurality of sound openings with a large aperture therein between the enclosure faceplate and the diaphragm and wherein the total area of the front face of the housing is close in size to the total area of the faceplate.

56. The hearing aid of claim 26 wherein the material is substantially acoustically transparent.
57. The hearing aid of claim 24 wherein the sound openings are smaller than about 40 mils in diameter.
58. The hearing aid of claim 24 wherein the sound opening range in size from about 15 to 30 mils in diameter.
59. The hearing aid of claim 24 wherein the sound openings are flared on the interior of the enclosure.
60. The hearing aid of claim 24 wherein the sound openings are flared on the exterior of the enclosure.
61. The hearing aid of claim 24 wherein the sound openings are flared both the exterior and interior of the enclosure.
62. The hearing aid of claim 5 wherein the printed circuit board is sealed to the housing by compliant adhesive.
63. The hearing aid of claim 62 wherein the printed circuit board is sealed to the housing by conductive epoxy.
64. The hearing aid of claim 5 wherein the printed circuit board is acoustically sealed by a pressure contact between the board and the housing using an intermediate member.

5

Sub  
a3

10

15

65. The hearing aid of claim 64 wherein the pressure contact is maintained by tabs extending from housing sidewalls and clamped onto a ground plane formed on an exterior side of the board.
- 5 66. The hearing aid of claim 5 in which the electrical connection comprises a ground plane on the printed circuit board which shields the interior of the housing from electromagnetic interference.
- Sub  
a3 67. The hearing aid of claim 40 including a second PCB disposed laterally adjacent the first PCB and wherein a JFET buffer is mounted on the first PCB.
- 10 68. The hearing aid of claim 67 wherein substantially all the electrical components required for a functional hearing aid other than a battery or a receiver are mounted on a substrate of the second PCB.
69. The hearing aid of claim 68 including a cover over the second PCB and electrically sealed to the housing about a periphery thereof.
- 15 70. A method of EMI shielding a microphone assembly containing electrical components comprising the steps of:  
housing the microphone assembly in an open ended metal cover;  
mounting components on a first side of a PCB opposite a second side containing a ground plane; and  
forming an electrical connection between a periphery of said cover and  
20 said ground plane.
71. The method of claim 70 wherein the connection is made by conductive epoxy.
72. The method of claim 70 wherein the connection is made by soldering.

73. The method of claim 70 wherein the connection is made by welding.
74. The method of claim 70 wherein the connection is made by pressure contact.
75. The hearing aid of claim 5 wherein the component on the first side of the PCB is a JFET buffer and other components are mounted on a side of the PCB opposite the first side.
76. The hearing aid of claim 75 wherein the PCB also forms an acoustic seal for a back chamber of the assembly.
77. The hearing aid of claim 76 wherein a further electrical connection is made from the JFET to component on the opposite side through a via on the PCB.
78. A method of forming a microphone assembly for a hearing aid comprising the steps of:
- providing a circular housing cover having an axially indented circular portion extending radially inward from the periphery of the cover;
  - inserting a diaphragm and annular support frame into the cover so that the frame contacts the indented circular portion, thereby providing a predetermined spacing between the cover and the diaphragm;
  - inserting a backplate into the cover so that a circular ridge extending radially inward about a periphery of the backplate abuts the periphery of the frame to establish a space between an inner central surface of the backplate and an adjacent surface of the diaphragm;
  - clamping the periphery of the backplate against the diaphragm and cover by a mounting ring which abuts the backplate.
79. The method of claim 78 wherein the mounting ring is press fit into an inner sidewall of the cover.

5

10

15

20

Sub  
a3

80. The method of claim 78 wherein a peripheral edge of the mounting ring is formed with projections which abut an inner sidewall of the housing and which collapse when an open end of the cover is sealed by an annular PCB extending across the open end.

5        81.    The hearing aid of claim 10 in which the buffer amplifier is a JFET mounted on a  
sidewall of the housing.

82. A microphone module for a hearing aid in which all the electrical components required for a functional hearing aid other than a battery and a receiver are contained along with a microphone in a single EMI shielded housing.

10 83. A microphone module for a hearing aid in which all the electrical components required for a functional hearing aid excluding a receiver and a main power source are contained along with a microphone and one or more supplemental cell power sources in a single EMI shielded housing.

84. The microphone module of claim 83 wherein the cell sources are electrochemical cells.

85. The microphone module of claim 83 wherein the cell sources are solar type cells.

86. The microphone module of claim 85 wherein the solar type cell sources comprise a solar cell array.

87. The microphone module of claim 83 wherein the components include an amplifier  
20 and at least one filter capacitor.

88. The microphone module of claim 87 including a voltage regulator.

Sub  
a3

89. The microphone module of claim 88 in which the voltage regulator is a zener diode.
90. The hearing aid of claim 6 in which the resilient member is gold plated.